


flexible LED FL-B50

flexible  LED

FOMEX[®]

In the box

FL-B50 Kit



LED Mat (25x25cm)



X-Mount Bracket



Dimmer




Power Supply



Power Cord(5m)




D-Tap(1.2m)



Kit Bag

How to connect

Please connect to power supply or V-Mount battery in the following order.



LED Mat (25x25cm)



Dimmer



Power Supply



Power Cord



D-Tap




V-Mount / Gold Mount
Battery

How to use Dimmer



- 1 Connect the LED Mat cable (1m) to dimmer output cable.
- 2 Connect DC power output jack to the dimmer when using the power supply or V-mount battery.
- 3 Adjust brightness with the DIM dial.
- 4 Select switch. ☀️ : Daylight, OFF : Turn OFF, 💡 : Tungsten

How to install X-Mount



- 1 Insert X-Mount in the rear corner of LED Mat Clips.
- 2 Install X-Mount on a stand or tripod after firmly fitted with LED Mat.

Specification

Model	FL-B50
Light Output	1500lux @1m: 3200K / 1600lux @1m: 5600k
Power Consumption	50W
CRI / TLCI	CRI 95 / TLCI 98
Color Temperature	3200K or 5600K
Dimmer	0~100% DIM / Manual
Light Output Connector	mini 4Pin XLR
DC Input	DC 15V, 4A
Beam Angle	120°
LEDs	240
Dimensions (mm)	250mm x 250mm
Weight	220g
Power Supply	Input : AC100 ~ 240V 50/60Hz Output : DC 15V, 4A, 60W