

# FreeStyle LED

# FreeStyle LED DMX



reeStyle LED has three menu options, one white and two color menus. With white light Kelvin range is from 2700K to 6500K with **Dimming**, **Kelvin** and **Green/Magenta** control channels. In the color menu, Kelvin range is from 2500K to 9900K, with three additional channels, **Gel**, **Hue Angle** and **Saturation**. The Gel channel includes Kino Flo presets such as blue & green screen and over 100 well-known lighting gels. In addition, the Hue Angle and Saturation behave similar to a traditional color wheel, where you have white light in the center, and the Hue angle determines the color along a 360° range, and Saturation determines how much color is applied. The second color menu provides individual red, green, blue (**RGB**) control. For additional versatility, the FreeStyle LED panel can be easily removed from the housing and mounted onto a stand. The controller comes with standard DMX, wireless DMX (Lumen Radio®), universal voltage input 100-240VAC and 24VDC. It can be mounted to the fixture or run remotely with a 25ft extension cable.

### Features include:

- Kelvin presets & custom settings, 2500K-9900K
- Dimming without color shift
- Green/Magenta control
- Dial in any color through Hue Angle and Saturation control
- Kino Flo presets and Gels
- Individual Red, Green, Blue (RGB) control
- Manual & DMX Dimming, DMX wireless (Lumen Radio)
- Removable fixture includes built-in Barndoors, Honeycomb Louver
- Twist-on, locking Center Mount and corner mount options
- KinoGrip Center Mount

### ▼ FreeStyle LED DMX Systems



FreeStyle 31 LED Fixture

CFX-F31

**CFX-F21** FreeStyle 21 LED Fixture

LED-1 50X-1 20U Select 150 LED DMX Controller, Univ 120U

LED-150X-230U Select 150 LED DMX Controller, Univ 230U



MTP-BG41 KinoGrip 41K Mount w/ Baby Receiver (16mm)



X12-25 Select 150 Extension, 25ft

## Photometrics

ErooCtudo 21	FC	510	161	75	43	28	20	15	11	9	8
FreeStyle 31	Feet	2	4	6	8	10	12	14	16	18	20
F. C.   01	FC	508	154	70	40	26	18	14	ņ	9	7
FreeStyle 21	Feet	2	4	6	8	10	12	14	16	18	20
ErrosChulo 21		7270	2470	11,90	683	445	312	233	181	146	ņ
FreeStyle 31		s 0.5	1	1.5	2	2.5	3	3.5	4	4.5	5
FreeStyle 21	LUX	7113	2409	1121	634	412	288	212	164	131	10
		s 0.5		1.5	2	2.5	3	3.5	4	4.5	5

Fixture Specifications					
Fixture	Kelvin Range	Dimming Range	Dimensions	Weight	
FreeStyle 3	1 2700~6500 2500~9900	100%~1%	40.5 x 3.5 x 11" w/ 6.5" barndoors (103 x 9 x 28cm w/ 16.5cm barndoors)	15 lb (7kg)	
FreeStyle 2	1 2700~6500 2500~9900	100%~1%	26.5 x 3.5 x 13" w/ 6" barndoors (67 x 9 x 33cm w/ 15cm barndoors)	11.5 lb (5kg)	

V LEI	LED Controller Specifications							
Controller	Input Voltage VAC	Amps VAC	Input Voltage VDC	Amps 24VDC	Kelvin Range	Dimming Range	Dimensions	Weight
LED-150X	100~240VAC, 50/60Hz, 150W	1.25A	18~36VDC, 150W	6.25A	2700~6500 2500~9900	100%~1%	15 x 4.5 x 3″ (38 x 11.5 x 8cm)	4.5 lb (2kg)
LED-150X	240~100VAC, 50/60Hz, 150W	0.65A	18~36VDC, 150W	6.25A	2700~6500 2500~9900	100%~1%	15 x 4.5 x 3″ (38 x 11.5 x 8cm)	4.5 lb (2kg)

## ▼ Details







## SYS-F31-120U FreeStyle 31 LED DMX System, Univ 120U

FreeStyle 31 LED DMX System, Univ 230U

SYS-F31-230U

## Contents

- 1 FreeStyle 31 LED Fixture
- 1 Select 150 LED DMX Controller
- 1 MTP-BG41 Mount w/ Baby Receiver (16mm)
- 1 Extension, 25ft



# SYS-F21-120U FreeStyle LED 21 DMX System, Univ 120U

SYS-F21-230U FreeStyle LED 21 DMX System, Univ 230U

# Contents

- 1 FreeStyle 21 LED Fixture
- Select 150 LED DMX Controller 1
- 1 MTP-BG41 Mount w/ Baby Receiver (16mm)
- 1 Extension, 25ft

▼ FreeStyle LED DMX Accessories/ Cases DFS-SL30-H










Select 30/31 Louver/HP, 60°



LVR-SL360-P



LVR-SL260-P Select 20/21 Louver/HP, 60°



LVR-FS340-S Select 30/31 SnapGrid, 40°

LVR-FS240-S Select 20/21 SnapGrid, 40°

MTP-L Kino 41 Lollipop w/ 3/8" Pin (10mm)



Baby Beceiver (16mm)

MTP-B41F

Kino Offset w/



STD-M36 Medium Duty, 36"

STD-M30



BAG-SL30 Select 30/31 Soft Case BAG-SL20 Select 20/21 Soft Case

KAS-DL30 Select 30/31 Flight Case KAS-DL20 Select 20/21 Flight Case

KAS-FS32 Gaffer 30/31 Ship Case (2-Unit) KAS-FS22 Interview 20/21 Ship Case (2-Unit)





Medium Duty, 30"

# FreeStyle LED DMX Kits

## ▼ FreeStyle 31 LED DMX Kits



**KITF31B-120U** FreeStyle 31 LED DMX Kit, Univ 120U w/ Soft Case

## KIT-F31B-230U

FreeStyle 31 LED DMX Kit, Univ 230U w/ Soft Case

Dimensions 42.5 x 7.5 x 16.5" (108 x 19 x 42cm) Weight 29 lb (13kg)
(1 3kg)



**KITF31-120U** FreeStyle 31 LED DMX Kit, Univ 120U w/ Flight Case

**KIT-F31-230U** FreeStyle 31 LED DMX Kit, Univ 230U w/ Flight Case

ContentsDimensions1FreeStyle 31 LED Fixture46 x 11 x 161Select 150 LED DMX Controller(117 x 28 x 4)1MTP-BG41 Mount w/<br/>Baby Receiver (16mm)Weight1Extension, 25ft49.5 lb1Flight Case(22kg)



KITF32-120U Gaffer/FS 31 LED DMX Kit, Univ 120U (2-Unit)

## KIT-F32-230U

Gaffer/FS 31 LED DMX Kit, Univ 230U (2-Unit)

	Contents	Dimensions
6.5″ 42cm)	<ol> <li>FreeStyle 31 LED Fixture</li> <li>Select 150 LED DMX Controller</li> <li>MTP-BG41 Mount w/ Baby Receiver (16mm)</li> <li>Extension, 25ft</li> <li>Ship Case</li> </ol>	43.5 x 13 x 18.5" (110.5 x 33 x 47cm) Weight 75 lb (34kg)

## ▼ FreeStyle 21 LED DMX Kits



**KIT-F21B-120U** FreeStyle 21 LED DMX Kit, Univ 120U w/ Soft Case

## KIT-F21B-230U

FreeStyle 21 LED DMX Kit, Univ 230U w/ Soft Case

### 1 FreeStyle 21 LED Fixture

- 1 Select 150 LED DMX Controller
- 1 MTP-BG41 Mount w/
- Baby Receiver (16mm) 1 Extension, 25ft
- 1 Soft Case
- (79 x 19 x 46cm) Weight 24.5 lb (11kg)

31 x 7.5 x 18"

Dimensions



**KITF21-120U** FreeStyle 21 LED DMX Kit, Univ 120U w/ Flight Case

# KIT-F21-230U

FreeStyle 21 LED DMX Kit, Univ 230U w/ Flight Case

Dimensions

FreeStyle 21 LED Fixture Select 1 50 LED DMX Controller	30 x 10.5 x 21" (76 x 27 x 53cm)
MTP-BG41 Mount w/ Baby Receiver (16mm)	Weight
Extension, 25ft Flight Case	39.5 lb (18kg)



KITF22-120U Interview/FS 21 LED DMX Kit, Univ 120U (2-Unit)

# KIT+F22-230U

Interview/FS 21 LED DMX Kit, Univ 230U (2-Unit)

Contents	Dimensions
<ol> <li>FreeStyle 21 LED Fixth</li> <li>Select 150 LED DMX</li> <li>MTP-BG41 Mount w/ Baby Receiver (16mr</li> <li>Extension, 25ft</li> <li>Ship Case</li> </ol>	Controller (91.5 x 33 x 52cm)



Kino Flo Lighting Systems 2840 North Hollywood Way Burbank, CA 91505 +1 818 767 6528 voice +1 818 767 7517 fax

www.kinoflo.com © Kino Flo FreeStyle LED No. 3110105 Rev B