



**QUASAR
SCIENCE**

Q-Lion

**Rechargeable
Lithium Ion
Battery LED**

Q5LS

Q10LS

Q20LS

Instructions

Operation:

- Press Power button once to turn on.
- Press Power button again to dim. Each button press dims to the next lower level.
100% 75% 50% 25% 10% 0%
- Double tap to turn off at any level.

- Press and hold Power button to change between 3000k and 5600k.

- Battery Level is shown with the indicator lights.
- Indicator lights will go to sleep after 10 seconds.
- Tap Power button once to wake and show battery level.

- To disable the Power Button when traveling, using a pen, press and hold the the KILL button button on the side for 5 seconds.
- To enable the Power Button after it has been killed, plug it into your charger.

- To Reset the lamp to default settings of 5600k and 100%, press the RST button.

Charging:

- The Q-Lion series V2.0 Lamp charges from a QC3.0 USB Charger rated 9V 2amp or 12V 1.5amp. The power light will flash if the charger is insufficient. (Lamp will not charge on a standard 5V USB charger.)
- The lamp cannot operate while charging.

www.QUASARSCIENCE.com