

## Affordable, Compact, Travel-Friendly

## **CUE-H135**

The **CUE-H135** V-Mount battery answers the power demands of digital cinematography and broadcast cameras where high current loads of 10.5A/135W are needed. The CUE-H135 is rated at a 134Wh capacity while keeping the dimensions of the previous CUE-D95. A single built-in 80W D-Tap output is standard to power accessories.



## **Product Features**



- Greater capacity than CUE-D95 with similar profile
- Meets passenger aircraft carry-on regulations
- 80W D-Tap to power accessories
- 4-LED Power Indicator
- Capable of handling up to 10.5A/135W loads
- Compatible with all ENDURA V-Mount chargers and accessories

## **Specifications**



Capacity:134WhMax Output Voltage16.8VNominal Voltage:14.8VMax Draw:10.5A

**Power Outputs:** (1) 80W D-Tap

End Voltage: 11.2V

**Additional Features**: 4-LED Power Indicator

**Protection:** Over-charge, over-discharge, over-current

**Ambient Temperature:** 32°F ~ 104°F (Charge), -4°F ~ 113°F (Discharge),

**Dimensions:** -4°F ~ 113°F (Storage)

Weight: 3.82(W) x 5.75(H) x2.32(D) inches

1.92 lbs

 $\ensuremath{\mathsf{IDX}}$  reserves the right to change the specifications contained herein without notice.



